

NEW Conext XW+ inverter/charger

One solution for global power needs

Conext™ XW+ is an adaptable single-phase and three-phase inverter/charger system with grid-tie functionality and dual AC power inputs. Available solar charge controllers, monitoring, and automated generator control modules enable further adaptability. From a single Conext XW+ unit to clusters up to 102 kW, the Conext XW+ is a scalable system that allows for the integration of solar capacity as required. Adaptable and scalable, the Schneider Electric™ Conext XW+ system is the one solution for grid-interactive and off-grid, residential and commercial, solar and backup power applications.

Why choose Conext XW+?



True bankability

- Warranty from a trusted partner with 178 years of experience
- World leader in industrial power drives, UPS and electrical distribution
- Strong service infrastructure worldwide to support your global needs



Higher return on investment

- Excellent load starting with high 30-minute and 5-second power
- Performs in hot environments up to 70°C
- Intelligent functionality enables solar prioritization, load shifting, peak shaving, and assists small generators with heavy loads
- Backup power with grid-tie functionality converts external DC power to AC power for export to the utility grid



Designed for reliability

- Extensive quality and reliability testing
- Highly Accelerated Life Testing (HALT)
- Globally proven and recognized field performance



Flexible

- Single or three phase systems from 7.0 kW to 102 kW
- Supports DC coupled and AC coupled off-grid and grid-tie architectures
- Supports charging of Lithium Ion battery packs



Easy to service

- Field serviceable with replacement boards and spare parts
- Monitor, troubleshoot or upgrade firmware with Conext ComBox



Easy to install

- System configures quickly into compact wall-mounted system
- Integrates both grid and generator power with dual AC inputs
- Balance of system components integrates battery bank, solar charge controllers and generators
- Commission the entire system with PC software tool and Conext ComBox



Product applications



Residential grid-tie solar with backup power




Self-consumption



Backup power



Community electrification



off-grid solar

Schneider
Electric™

Device short name	XW+ 7048 E	XW+ 8548 E
Inverter AC output		
Output power (continuous) at 25°C	5500 W	6800 W
Overload 30 min / 60 sec at 25°C	7000 W / 9500 W	8500 W / 12000 W
Output power (continuous) at 40°C	4500 W	6000 W
Maximum output current 60 seconds (rms)	40 A	53 A
Output frequency (selectable)	50 / 60 Hz	50 / 60 Hz
Output voltage	230 Vac	230 Vac
Total harmonic distortion (THD) at rated power	< 5%	< 5%
Idle consumption search mode	< 7 W	< 7 W
Input DC voltage range	40 to 64 V (48 V Nominal)	40 to 64 V (48 V Nominal)
Maximum input DC current	150 A	180 A
Charger DC output		
Maximum output charge current	110 A	140 A
Output charge voltage range	40 - 64 V (48 V Nominal)	40 - 64 V (48 V Nominal)
Charge control	Three stage, two stage, boost, custom	Three stage, two stage, boost, custom
Charge temperature compensation	Battery temperature sensor included	Battery temperature sensor included
Power factor corrected charging	0.98	0.98
Compatible battery types	Flooded (default), Gel, AGM, LiON, custom*	Flooded (default), Gel, AGM, LiON, custom*
Battery bank range (scaled to PV array size)	440 to 10000 Ah	440 to 10000 Ah
AC input		
AC 1 (grid) input current (selectable limit)	3 - 60 A (56 A default)	3 - 60 A (56 A default)
AC 2 (generator) input current (selectable limit)	3 - 60 A (56 A default)	3 - 60 A (56 A default)
Automatic transfer relay rating / typical transfer time	60 A / 8 ms	60 A / 8 ms
AC input voltage nominal	230 V +/- 3%	230 V +/- 3%
AC input frequency range (bypass/charge mode)	45-55 Hz (default) 40-68 Hz (allowable)	45-55 Hz (default) 40-68 Hz (allowable)
AC grid-tie output		
Grid sell on AC1 (max)	4.5 kVA	6.0 kVA
Grid sell current range on AC1 (selectable range)	0 to 20 A	0 to 27 A
Grid sell voltage range on AC1	205 to 262 Vrms (auto adjust entering sell mode)	205 to 262 Vrms (auto adjust entering sell mode)
Grid sell frequency range on AC1	48 to 51 Hz (auto adjust entering sell mode)	48 to 51 Hz (auto adjust entering sell mode)
Grid sell power factor range (lead/lag)	0.5	0.5
Efficiency		
Peak	95.8%	95.8%
General specifications		
Part number	865-7048-61	865-8548-61
Product / shipping weight	53.5 kg (118.0 lb) / 75.0 kg (165.0 lb)	55.2 kg (121.7 lb) / 76.7 kg (169.0 lb)
Product dimensions (H x W x D)	58 x 41 x 23 cm (23 x 16 x 9 in)	58 x 41 x 23 cm (23 x 16 x 9 in)
Shipping dimensions (H x W x D)	71.1 x 57.2 x 39.4 cm (28.0 x 22.5 x 15.5 in)	71.1 x 57.2 x 39.4 cm (28.0 x 22.5 x 15.5 in)
IP degree of protection	IP20	
Operating air temperature range	-25°C to 70°C (-13°F to 158°F) (power derated above 25°C (77°F))	
Warranty (Depending on the country of installation)	2 or 5 years	2 or 5 years
Features		
System monitoring and network communications	Available	
Intelligent features	Grid sell, peak load shave, generator support, prioritized consumption of battery or external DC energy	
Auxiliary port	0 to 12 V, maximum 250 mA DC output, selectable triggers	
Off-grid AC coupling	Frequency control	
Multi-unit operation	Single phase: up to four units in parallel, three phase: up to 12 units in multi-cluster configuration with external AC contractor	
Regulatory approval		
CE marked according to the following EU directives and standards:		
EMC directive	EN61000-6-1, EN61000-6-3, EN61000-3-2	
Low voltage directive	EN50178	
Safety	IEC 62109-1, IEC 62109-2	
RCM marked and compliant	AS 4777.2, AS 4777.3	

Specifications are subject to change without notice.

Conext XW+ works with the following Schneider Electric products



XW+ Power Distribution Panel
(without AC Breakers)
Product no. 865-1014-01



Conext System Control Panel
Product no. 865-1050-01



Conext Automatic Generator Start
Product no. 865-1060-01



MPPT 60 150 solar charge controller
Product no. 865-1030-1



MPPT 80 600 solar charge controller
Product no. 865-1032



Conext Combox communication device
Product no. 865-1058



Conext Battery Monitor
Product no. 865-1080-01



Conext Battery Fuse Combiner Box 250
Product no. 865-1031-01

XW Configuration Tool
Product no. 865-1155